

ТЕХНИЧЕСКАЯ СПЕЦИФИКАЦИЯ

ITDAN-PR2

Dante - аналог (приемник)



Конвертор Dante - аналог (приемник)

Обзор

Конвертор из Dante в аналоговый аудиосигнал, с разъёмами Phoenix (6pin). Не требует установки драйверов и программного обеспечения. Поддерживает 2 выходных канала аудио. Компактный дизайн и высокая производительность, питание от PoE.

Функции

- Аналоговый аудиовыход поддерживает балансный/небалансный аудиовыход (небалансный доступ к "+" и "GND")
- Частота дискретизации аудио поддерживает 44,1 кГц, 48 кГц и 96 кГц (24 бит)
- Решение Dante поддерживает передачу звука по протоколу AES67 RTP
- Аудио выход поддерживает 3-уровневую регулировку усиления: +18dBu, 0dBu (по умолчанию) и -10dBV
- Поддержка источника питания DC 12V и функции POE (IEEE802.3af Class 0)

Video Network Bandwidth	100M
Audio Formats	PCM 2.0 44.1kHz/48kHz/96kHz, up to 24bit
Transmission Distance	100m (CAT6/6A)
Inputs	1x DANTE [RJ45 connector, POE] 1x PWR [2-pin phoenix, 3.81mm]
Output	1x AUD [6-pin phoenix, 3.81mm]
Housing	Metal Enclosure
Color	Black
Dimensions	120mm[W] x 47mm[D] x 26mm[H]
Weight	186g
Power Supply	DC input: 12V POE input: IEEE802.3af Class 0
Power Consumption	1.32W
Operation Temperature	32 – 104°F / 0 – 40°C
Storage temperature	-4 – 140°F / -20 – 60°C
Relative Humidity	20 – 90% RH (no condensation)
Control Method	Dante Controller